


# Item No.: HS13B-1

## Operation Instruction

### 1. Product Outline



### 2. Product Specification

Bottom introduction: There are seven buttons that "▲", "▼", "1", "2", "人", "人", "M"

- (1) "▲" : Adjust the desk upwards
- (2) "▼" : Adjust the desk downwards
- (3) "1" : Position 1, first height position saved by the user
- (4) "2" : Position 2, second height position saved by the user
- (5) "人" : the display shows "3", which means the position of the standing height the user saved.
- (6) "人" : the display shows "4", which means the position of the standing height the user saved.
- (7) "M" : Height saving button, for height memory function; Child lock: for security

### 3. Operating Instructions

- Child lock function:
  - a. To lock and unlock, touch and hold the M button for about 5 seconds. When the lock is on, the indicator light above "▼" and M will turn blue.

- b. When the lock is on, the indicator light will flash once when other buttons are touched.
- c. All the buttons works only when the lock is off.

- Height Adjustable Function:

Press the "▲" or "▼" button to adjust the height. The LED display shows the current height.

- Height Memory Function:

a. Press UP or DOWN button and adjust the height to the desired height. Press "M" to save the height, and the screen will display "5-";

Press "1", "2", or " f ", " 3 " then, that is, save the height to the corresponding position 1 or 2 3, or 4, which will show in the display screen as "5-1", "5-2", or "5-3", or "5-4";

b. Press "1", "2" and " f ", " 3 "button directly to automatically adjust the memory height you saved.

- USB charging function:

a. USB output: QC2.0/QC3.0, 5.0v / 9.0v / 12.0v, ±5%, current: 1.0a

- Collision prevention sensitivity adjustment - optional features:

a. Press and hold the "▲" "▼" button for 5 seconds at the same time to switch the sensitivity. There are four levels of sensitivity (A-3, A-2, A-1, A-0). Each operation will switch the sensitivity into the next level.

b. The display shows "A-0", the anti-collision function is off; the display shows "A-1", low sensitivity; Display shows "A-2", medium sensitivity; display shows "A-3", high sensitivity; (factory default is A-3);

c. During height adjustment, when tabletop comes in contact with another object, it instantly stops and reverses to avoid damage.

d. Press and hold the "▲" "▼" button for 5 seconds at the same time. If the display does not display the above code, there is no anti-collision function.

- Troubleshooting:

a. Reset: When the LED shows "RSF", press "▼" button until the desk reaches its lowest height and rebounds to stop, it means the reset has been finished.

b. When it doesn't work and the LED shows "E01" or "E02", please retry 18 mins later.

c. If the "▼" button doesn't work, please check the cable connection and then cut off the power for at least 10 seconds. Reconnect to the power and press "▼" button to start the reset process when it shows the "RSF".

d. If all these above process are inefficient, please contact our customer service.

#### Waste disposal



This marking indicates that this product should not be disposed with other household wastes. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.